

6-18GHz Broadband Power Divider

Product Overview

AT Microwave offers high performance and broadband power divider from DC-67GHz, with SMA, SMA, 2,4mm and 1.85mm connectors.

Based on our excellent design work, precise machine tolerance and outstanding quality plating, we can provide band pass filter with low insertion loss, good return loss and high rejection at the same time.

More information, please visit www.atmicrowave.com



Advantages

- ✓ Broadband Performance
- ✓ Low Insertion Loss
- ✓ Good Amplitude and Phase balance
- ✓ Good Return Loss

Application

- ✓ 5G Communication
- ✓ Test Equipment
- ✓ ROF (RF Over Fiber)
- ✓ Radar System

Key Features

Parameter	Min	Typical	Max
Frequency Range		6-18GHz	
Normal Power Splitting		9dB	
Normal Phase Shift		0 Degree	
Insertion Loss		-1.2dB	-2.5dB
Amplitude Balance		+/-0.4dB	+/-0.8dB
Phase Balance		+/-5 Degree	+/-10 Degree
VSWR		1.5:1	2.0:1
Isolation	15dB	20dB	
CW Power Forward			30W
CW Power Reverse			1W
Spec Temp		25C	





AT-PD8-0618

6-18GHz Broadband Wilkinson Power Divider

Mechanical Information

Item	Description
Input Port	SMA Female
Output Port	SMA Female
Case Material	Aluminum
Finish	Painted
Weight	180g
Size:	See outline

Absolute Maximum Ratings Table


Parameter	Value
RF Input Power CW Forward	30W
RF Input Power CW Reverse	1W
Operating Temperature	-40 to + 85C
Storage Temperature	-65 to +125C

Notes:

1. Datasheet may be changed according to update of MMIC, Raw materials , process, and so on.
2. This data is only for reference, not for guaranteed specifications.
3. Please contact AT Microwave team to make sure you have the most current data.



Test Data:



Dimension: (unit in mm)

